

USB 3.0 Dual Video Docking Station

User Manual

Ver. 1.00

**All brand names and trademarks are properties of their
respective owners.**

Contents:

Chapter 1: Introduction	3
1.1 Product Introduction	3
1.2 Features.....	3
1.3 System Requirements	4
1.4 Package Contents.....	4
1.5 Hardware Layout	5
Chapter 2: Getting Started	6
2.1 Driver Installation.....	6
2.1.1 Installation for Windows.....	6
2.1.2 Installation for Mac OS X.....	7
2.2 Hardware Installation	8
2.3 Verifying the installation.....	10
2.3.1 Verifying for Windows.....	10
2.3.2 Verifying for Mac OS X.....	11
2.4 Display Configuration	12

Chapter 1: Introduction

1.1 Product Introduction

This USB 3.0 Dual Video Docking Station is designed to expand connectivity to your Ultrabook™ or Hybrid tablet/laptop via single USB 3.0 port. It features dual display ports (1 HDMI and 1 DVI) to enable your system's display capability, supporting HD resolution and multiple display modes including primary, extended and mirrored. This USB 3.0 Dual Video Docking Station offers 2 USB 3.0 ports to satisfy multiple device connectivity needs.

1.2 Features

- Easy Installation
- An ideal solution for expanding the connectivity of Laptop, Ultrabook and Macbook
- Adds dual displays and 2 USB 3.0 ports to your USB 3.0 enabled system
- Compatible with SuperSpeed USB 3.0 and backwards compatible

with USB 2.0 specification

- Extended Desktop (Default), Mirror Desktop, Primary Display
- High resolutions for display up to 2048 x 1152


1.3 System Requirements

- Windows® XP 32-bit, Vista/7/8/8.1 (32/64 bit); Mac OS X 10.6 or above
- Available USB port (USB 3.0 recommended)

1.4 Package Contents

- 1 x USB 3.0 Dual Video Docking Station
- 1 x User Manual
- 1 x Driver CD

1.5 Hardware Layout



1. **DVI output port:** Connect to a DVI monitor
2. **HDMI output port:** Connect to a HDMI monitor
3. **USB 3.0 downstream ports:** Connect USB peripheral devices
4. **Power jack:** Connect to the optional power adapter
5. **Power indicator:** Lights up when the power is on
6. **USB 3.0 upstream cable:** Connect to the USB 3.0 port of the host computer

Chapter 2: Getting Started

2.1 Driver Installation

Follow the procedures below to install the driver and then connect the USB 3.0 Dual Video Docking Station to your system.

2.1.1 Installation for Windows

1. Insert the provided CD into your disk drive. The CD-ROM will start automatically. The following screen will show up and please click “**Install Driver**”.




*Note: Actual image may vary

Note: If the install program doesn't run automatically, please locate and double-click on the **Autorun.exe** file in the CD to

launch the install program.

2. Please wait while Windows configures DisplayLink Core Software. Your screens may temporarily go black or flashing during this process.




3. When finished, the installation screen will disappear and you will return to your desktop.

Note: On some machines, you may need to reboot before you can use USB 3.0 Dual Video Docking Station.

2.1.2 Installation for Mac OS X

1. Insert the provided CD into your CD-ROM drive.
2. Double-click the “**U3 Dock**” disc icon, double-click package file “**mac.dmg**”, the following “U3 Dock” virtual disk will be appeared on the Desktop of your Mac OS X system. Then double

click “Drivers” folder.



3. Select “**DisplayLink Software Installer**” to begin installing the DisplayLink Driver on your Mac.



4. Follow the instructions on screen to install the driver. After driver installation is complete, you must restart your computer.


2.2 Hardware Installation

1. (Optional): Plug the power adapter into the power jack of the

Docking Station.

2. Connect the USB 3.0 Dual Video Docking Station:

Connect the USB 3.0 Dual Video Docking Station to an available USB 3.0 on the host computer. Then a pop-up message will appear in the notification area indicating the installation is complete.



* Actual strings depend on your operation system. This screen shot is from Windows 7 and might vary slightly for each operating system.

3. Connecting HDMI monitor

- Use a HDMI cable (not provided) to connect the HDMI port to a monitor equipped with HDMI input jack

4. Connecting DVI monitor

- Use a DVI cable (not provided) to connect the DVI port to a monitor equipped with DVI input jack

5. Connecting USB 2.0/USB 3.0 device

Connect your USB device to the USB 3.0 port on the Docking Station. As long as one USB device is connected to the port and

the connection works properly.


2.3 Verifying the installation

2.3.1 Verifying for Windows

1. Click on the “**Device Manager**” tab in the Windows Control Panel.

Start > Control Panel > Device Manager


2. In the **USB Display Adapters** group, an item named **Displaylink USB 3.0 dock** should be displayed.



Note: If there is a question or exclamation mark next to that item, then the driver is not properly installed. Please delete the item, select the **Delete the driver software for this device** option (if provided), unplug the USB 3.0 Dual Video Docking Station from your computer and then repeat the installation steps.

2.3.2 Verifying for Mac OS X

1. Choose About this Mac from the Apple menu.
2. Click on More Info...
3. In the Contents sidebar select USB from the Hardware section.
4. Scroll the list to reveal the USB 3.0 Dual Video Docking Station information




2.4 Display Configuration

When USB 3.0 Dual Video Docking Station is attached, an icon appears in the taskbar. This gives you access to the DisplayLink manager menu.

To use the DisplayLink Manager Menu

1. From the taskbar, click the DisplayLink icon 
2. A menu appears with several options. These are shown and described below.



- **Screen Resolution:** Click to select an available resolution. Note: This function is disabled in mirror mode, as the resolution is defined by the resolution of the primary monitor
- **Screen Rotation:** Rotates the screen according to the desired orientation
- **Extend to:** Extends the screen according to the desired orientation
- **Extend:** This is the default settings of the USB 3.0 Dual Video Docking Station. This mode extends your desktop for easy

viewing of multiple windows. The window will move off the primary display from the right side and enter the extended display from the left side

- **Set as Main Monitor:** Sets the extended screen as the main screen
- **Mirror:** Duplicates the primary monitor to the monitor which connects with the USB 3.0 Dual Video Docking Station
- **Off:** Turns off the USB 3.0 Dual Video Docking Station
- **Optimize for Video:** Optimize the video quality when playing back. Text may appear less clear when enabling
- **Fit to TV:** Adjusts the size of the desktop on the TV. Note: This function works only when one display is connected